

Celadon Inc.

RCV-5000 IR to RS-232 Output Table

Device: Zenith Plasma Display Monitor; Model: 42 inch, 60 inch

Infrared Remote Control: Philips PRONTO, Niles Intellicontrol

Infrared Code Format: NEC - Device ID: 7B02

Infrared Pronto Data File(s): See "IR Code Read Me - RCV-5000.txt" for complete description

Infrared Receiver: Celadon RCV-5000 Infrared to RS-232 Receiver

RCV-5000 Data File: zenith1_r.hex

Data: 2400 Baud, 8, N, 1, ASCII Output

Standard Transmit and Receive Pinout

Zenith Function	Pronto Button	RCV-5000 Output
Power ON	0	p 0 1
Power Off	1	p 0 0
Input RGB	2	i 0 0
Input AV (Video)	3	i 0 1
Input Component	4	i 0 2
Input S-AV (S-Video)	5	i 0 3
Aspect Ratio Wide Screen (16:9)	6	r 0 0
Aspect Ratio Normal Screen (4:3)	7	r 0 1
Aspect Ration Full Screen (Zoom)	8	r 0 2
Screen Mute ON	9	m 0 0
Screen Mute OFF	10	m 0 1
Volume Mute ON (volume off)	11	w 0 0
Volume Mute OFF (volume on)	12	w 0 1
PIP off	13	z 0 0
PIP small	14	z 0 1
PIP large	15	z 0 2
PIP Input AV (Video)	16	e 0 0
PIP Input Component	17	e 0 1
PIP Input S-AV	18	e 0 2

Celadon, Inc.

50 Mitchell Blvd.

San Rafael, CA 94903

Sales: (707) 648-1098

Main Tel: (415) 472-1177

Main Fax: (415) 472-1179

sales@celadon.com